

FVW3030-0600

VIDEO 2-WIRE

FRONT-DOOR STATION ADAPTER



VIDEO
2
DRAHT

The FVW3030-0600 is an adapter for coupling video front-door stations in 6-wire BUS technology to the video 2-wire:BUS power supply unit NVV1000-0400.

Article no.

Video 2-wire
Front-door station adapter

[FVW3030-0600](#)

FVW3030-0600

PRODUCT FEATURES

- > Video 2-wire:BUS supply from the NVV1000
- > Can be used for TCS front-door stations of the AVD/AVE, AVU, AMI (except AMI10105-0710/-0757) and KTU series
- > Can be used for TCS audio front-door stations in combination with selected video cameras from TCS
- > Frequency modulation of the video signal on the video 2-wire:BSU
- > Polarity-free av and bv
- > Compatible with the TCS:BUS protocol
- > Rested according to DIN EN 50486
- > Type of housing: ABS plastic built-in housing, blue

TECHNICAL DATA

- > Supply voltage (video 2-wire:BUS):
32 V DC +2 V / -6 V from the NVV1000-0400
- > Current consumption (video 2-wire:BUS):
I(a in standby) = 2.4 mA, I(Pv) in standby = 10.3 mA
- > 6-wire output: I (P out) max. 400 mA
- > Protection category: IP20
- > Weight: 30 g
- > DIN-rail case H x W x D mm: 52 x 52 x 23
- > Acceptable ambient temperature: -25 to +55°C



<http://www.tcsag.de/en/products>

SYSTEM EXAMPLE ON NVV1000

	Number of V2D indoor stations	
	IVW5211	IVH4222
With video front-door station (incl. FVW3030)		
With AVD/AVE	24	24
With AVU (2-slot)	12	24
With audio front-door station and separate camera (incl. FVW3030)		
With ASI11000-00xx + FVK32xx-0	24	24
With ASI11000-00xx + FVK22xx-0	24	24

A maximum of five video distributors, 2-way (FVY2200-0600), are permitted in the active speech channel.

CONTACTS

For design queries, please contact the technical hotline

Phone +49 (0)4194 9881-188
(German landline)

Please direct your queries to

Fax +49 (0)4194 9881-189
E-mail hotline@tcsag.de